

Description:

- Daily Check
- High Voltage Value (up to $\pm 35\text{KV DC}$)
- Accuracy: DC volts: $\pm 2\%$ up to $\pm 35\text{kV}$
- Easy use & Safety operation



Specification:

Voltage division ratio: 1000:1

Working HV : $\pm 35\text{KV DC}$ (Max. 39.9KV)

Environment coefficient : $< 200\text{ppm}/^\circ\text{C}$

Dimension : 400*180*80mm

Power supply: 100V-240VAC input / DC 5V,1A output

Display Accuracy : $\pm 2\%$

Operation temperature : 0°C to $+ 50^\circ\text{C}$

Weight : 1.1kg

Ground Clip lead : 1.6 meter.

Operation

Easy use and safety operation. Power on the **RESD1** and connecting the ground clip Lead **before** use. High voltage source direct touch to the measure tip without any measure range select which max. high voltage can be measured up to $\pm 35\text{KV DC}$

Safety precautions

The RESD1 ESD High Voltage meter must only be used by personal who are trained experienced and who are trained in safety precautions that are necessary to avoid possible injury when using such a device.

Hands, shoes, floor and work bench must be dry. Avoid making measurements under humid, damp or environmental conditions that might affect the safety of the measurement situation. The meter body should be kept clean and free of any conductive contamination.

WARNING

The ground clip lead connection is critical to the safe operation of the meter at any time.

台灣公司：利諾科技有限公司

23145 新北市新店區寶橋路235巷130號6樓之5

www.richtec.com.tw Tel: 886-2-89121185 Fax: 886-2-89121812 E-mail: rich.tec@msa.hinet.net

大陸公司：昆山盈軒电子科技有限公司

昆山市玉山镇新南中路567号1号楼A栋1919室 215300

www.ksyet.com

Tel: 0512-57350498

Fax: 0512-57350478

E-mail: info@cwintek.com